








1	General information	Supplier's name or trade mark	Inspire		
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS00001, 59790 RONCHIN		
3		Model Identifier - Luminaire Supplier reference	OS-L3M		
4		Light sources maker model	TL5905MD		
5		Date of placement on the market	01/01/2022		
6	Type of light source:	Lighting technology used:	LED		
7		Light source cap type (or other electric interface)	Internal wire		
8		Non-directional (NDLS) or directional (DLS):	NDLS		
9		Mains (MLS) or non-mains (NMLS):	NMLS		
10		Connected light source (CLS):	no		
11		Colour-tunable light source:	no		
12		Envelope:	no		
13		High luminance light source:	no		
14		Anti-glare shield:	no		
15		Dimmable:	only with specific dimmers		
16	General product parameters:	Energy consumption in on-mode (kWh/1000 h)	2	kWh/1000h	
17		Energy efficiency class	D		
18		Useful luminous flux (Φ_{use}), indicating if it refers to the flux in a sphere (360°), in a wide cone (120°) or in a narrow cone (90°), expressed in Lm	300	360	
19		Correlated colour type	single value		
20		Correlated colour temperature, rounded to the nearest 100 K, or the range of correlated colour temperatures, rounded to the nearest 100 K, that can be set	4000 K		
21		On-mode power (P_{on}), expressed in W and rounded to the first decimal	1.8	W	
22		Standby power (P_{sb}), expressed in W and rounded to the second decimal	0.00	W	
23		Networked standby power (P_{net}) for CLS, expressed in W and rounded to the second decimal	0.00	W	
24		Colour rendering index, rounded to the nearest integer, or the range of CRI-values that can be set	80		
25		Outer dimensions without separate control gear, lighting control parts and nonlighting control parts, if any (millimetre)			
26		Height (mm)	61.00	mm	
27		Width (mm)	61.00	mm	
28		Depth (mm)	1.00	mm	
29		Spectral power distribution in the range 250 nm to 800 nm, at full-load (insert picture of the spectral power distribution + name of picture+extension (.jpeg))	OS-L3M spectral power distribution.jpg 		
30		Claim of equivalent power	yes		
31	If yes, equivalent power (W)	28	W		
32	Chromaticity coordinates (x and y)	0.380; 0.380			
33	Parameters for directional light sources:	Peak luminous intensity (cd)	cd		
34		Beam angle in degrees (no decimal), or the range of beam angles that can be set	Degrees		
35	Parameter for LED and OLED light sources:	R9 colour rendering index value			
36		Survival factor rounded to the second decimal (>0.xx)	0.90		
37		Lumen maintenance factor rounded to the second decimal (>0.xx)	0.96		
38	Parameters for LED and OLED mains lights sources:	displacement factor (cos ϕ_1) rounded to the second decimal	0.00		
39		Colour consistency in McAdam ellipses	6.0		
40		Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage.	-		
41		If yes then replacement claim (W) (no decimal)	W		
42		Flicker metric (Pst LM) rounded to the first decimal	0.0		
43		Stroboscopic effect metric (SVM) rounded to the first decimal			
44	Technical documentation name (in case of light source product)				
45	Light source removing instruction name (in case of containing product)				

LIGHT SOURCE REMOVING INSTRUCTION		Creation date (dd/mm/yyyy) :	23/11/2021
		Last update date (dd/mm/yyyy) :	23/11/2021
1	General information	Supplier's name or trade mark	ADEO Services,
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS0001, 59790 RONCHIN
3		Model Identifier - Luminaire Supplier reference	OS-L3M
4		Light sources maker model	TL5905MD

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

	Explanation of the step	Pictures	Tools
Step 1	Unscrew the glare cover.		by hand
Step 2	Take off the dazzling cover, transparent cover pressing block, and transparent cover in turn.		by hand
Step 3	Loosen the two screws of the junction box cover with an electric screwdriver.		electric screw driver
Step 4	Take out the junction box and take out the junction box cover. Pull out the battery connector by hand, take out the battery.		by hand
Step 5	Pull out the connector of the light board by hand.		by hand
Step 6	Take out the light board by hand, the disassembly of the light board is completed		by hand
Step 7			

Step 8			
Step 9			
Step 10			

相对光谱

1.0 = 6.374e+000mW/nm

