	ノる	PRODUCT INFORMATION SHEET (ANNEX 5)	Creation date (dd/mm/yyyy) :	2021/7/16	
1	ç	Supplier's name or trade mark	Last update date (dd/mm/yyyy) :	2021/7/16	
2	General information	Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS00001, 59790 RONCHIN		
	infor	Model Identifier - Luminaire Supplier reference		J9790 KONCIIIN	
	enera	Light sources maker model	DE13112-WHITE,DE13112-BLACK 59-03#		
	O	Date of placement on the market	01/09/2021		
_		<u> </u>	LED LED		
$\dashv$		Lighting technology used:	no		
		Light source cap type (or other electric interface)  Non-directional (NDLS) or directional (DLS):	NDLS		
-	ài		NMLS		
)	sourc	Mains (MLS) or non-mains (NMLS):	no		
	Type of light source	Connected light source (CLS):			
-	pe of	Colour-tuneable light source:	no no		
!	₽	Envelope:			
		High luminance light source:	no		
		Anti-glare shield:	no		
		Dimmable:	no	1	
		Energy consumption in on-mode (kWh/1000 h)	5	KWh/1000h	
		Energy efficiency class  Useful luminous flux (Физе), indicating if it refers to the flux in a sphere (360°), in a	D	1	
		wide cone (120°) or in a narrow cone (90°), expressed in Lm	660 lm in sphere	360	
		Correlated colour type	single value	1	
		Correlated colour temperature, rounded to the nearest 100 K, or the range of correlated colour temperatures, rounded to the nearest 100 K, that can be set	3000	К	
		On-mode power (Pon), expressed in W and rounded to the first decimal	4.5	W	
		Standby power ( $P_{sb}$ ), expressed in W and rounded to the second decimal	0.00	W	
:		Networked standby power (Pnet) for CLS, expressed in W and rounded to the second decimal	0.00	W	
ļ	ió	Colour rendering index, rounded to the nearest integer, or the range of CRI-values that can be set	80		
5	General product parameters:	Outer dimensions without separate control gear, lighting control parts and nonlighting control parts, if any (millimetre)			
ò	para	Height (mm)	44.15	mm	
,	oduct	Width (mm)	126.00	mm	
3	ral pr	Depth (mm)	1.20	mm	
	Gene	Spectral power distribution in the range 250 nm to 800 nm, at full-load (insert picture of the spectral power distribution + name of picture+extension (.jpeg)			
		, , ,	Spectrum 1.0=14.153eW/nn 1.2		
			0.8-		
9			0.6-		
			0.4-		
			0.2-		
			10.380 480 580 680 780 Mavelength(na)		
_		Claim of equivalent power	yes	1	
		If yes, equivalent power (W)	51	W	
	10 -	Chromaticity coordinates (x and y)	0.440; 0.403		
	Parameters directional light sources:	Peak luminous intensity (cd)		cd	
	Parar direc lig sou	Beam angle in degrees (no decimal), or the range of beam angles that can be set	0	Degrees	
	for SLED ces:	R9 colour rendering index value	1	_	
	Parameter for LED and OLED light sources:	Survival factor rounded to the second decimal (>0.xx)	0.90		
	Para LED i	Lumen maintenance factor rounded to the second decimal (>0.xx)	0.95		
		displacement factor (cos φ1) rounded to the second decimal	0.00		
,	nd OL ces:	Colour consistency in McAdam ellipses	6.0		
)	Parameters for LED and OLED mains lights sources:	Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage.			
_		If yes then replacement claim (W) (no decimal)	0.0	W	
2	netera	Flicker metric (Pst LM) rounded to the first decimal	0.0		
3	Paran	Stroboscopic effect metric (SVM) rounded to the first decimal	0.0		
ı		Technical documentation name (in case of light source product)			
		Light source removing instruction name (in case of containing product)			

1 adeo		LIGHT SOURCE REMOVING INSTRUCTION	Creation date (dd/mm/yyyy) :	2021/7/16	
	QUALITY		Last update date (dd/mm/yyyy) :	2021/7/16	
1	neral informati	Supplier's name or trade mark	INSPIRE		
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS0001, 59790 RONCHIN		
3		Model Identifier - Luminaire Supplier reference	DE13112-WHITE,DE13112-BLACK		
4		Light sources maker model	59-03#		

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

	Fundamental of the atom	Disturce	Tools
Ston 1	Explaination of the step	Pictures	Tools
Step 1	The screwdriver removes the plastic cover		screwdriver
Step 2	Light source for SLR testing		hand
Step 3			
Step 4			
Step 5			
Step 6			
Step 7			
Step 8			
Step 9			